



# How To

## Service Documents from APPI


**Document: #HT000174**

**Document Title: Set Up Loftware 10.2 with Seagull Scientific Printer Driver**

**Product(s): Any TIZ Printer**

### Foreword:

These settings are for Loftware 10.2. This document assumes that a printer driver, such as ZDesigner or Seagull Scientific has already been set up, and that the bagger printer already is listed under Devices and Printers.





# How To


## Service Documents from APPI

### Procedure:

#### *Loftware Printer setup – Printer Wizard*

---

Go to Printer Wizard



Click Next



# How To

## Service Documents from APPI

**Device** will set a number automatically depending on how many printers have already been set up.

**Family** should be Zebra.

In Loftware, there are no direct settings for the Zebra 110Xi4. Instead, choose ZPLII in **Model**.

Alias can be whatever you want.

Click **Options**.

Configuration - Device 2: Alias can be whatever you want (Zebra ...)

**Step 1:**  
Select Family, Model, and Alias

The First step when configuring a device is to select the Family and Model of the device you would like to configure.

The device Alias allows you to give the device a unique name, for example 'Shipping 1'.

If you enter an Alias you have used before you are then prompted to re-enter the Alias.

Device #: 2

Family: Zebra

Model: ZPLII

Alias: Alias can be whatever you want

Options...

< Back Next > Cancel Help

Options will bring up this window. Change the settings as shown in the next picture.

Options: Device 2: Zebra ZPLII

ZPLII Printer Options

Print Mode: Tear Off

Media: Thermal Transfer

Backfeed: Default

Stock Type: Non-Continuous

Character Set: USA 1

DB Char Set: Unicode UTF-16

Download Graphics To: DRAM

Cut Interval: 0

Tear Off: 0

Always Download Format

Override Pause Count

Ignore Printer Status

Use ZPL II

Z64 Compression

Only re-send fields that have changed

Send Options (Label/Printer)

Global Printing Engine

Recall True Type Font

Recall True Type Font

Advanced Text Properties

Default Glyph

Bidirectional Text Layout

Character Shaping

OpenType Table Support

Custom Command

ZPL command:

Send Command: Alter ZPL Control Strings

Real Time Clock

Field Clock Indicators:

Set Date/Time

Set Clock Offset

OK Cancel Printer Status Help



# How To

## Service Documents from APPI

**Print Mode:** Rewind

**Media:** Thermal Transfer

**Backfeed:** Default (for this print mode, which is no back feed)

**Stock Type:** Continuous

Click **OK**

The **Options** window will close, and this window will be back up again.

Click **Next**.



# How To

## Service Documents from APPI

This window will show Change **Port Type** as necessary.

Configuration - Device 2: Alias can be whatever you want (Zebra ...)

**Step 2:**  
Select Port Type and Port

The next step when configuring a device is to select a Port for the device you would like to configure.

When choosing a Port you must first select the type of Port this device will print to.

The list of Ports will vary depending on the Port type selected.

Port Type:  Select Port:

< Back Next > Cancel Help

If you are using a wired/wireless network card in the bagger, you can use **TCP/IP**.

If choosing **TCP/IP**, IP Address is necessary

Configuration - Device 2: Alias can be whatever you want (Zebra ...)

**Step 2:**  
Select Port Type and Port

The next step when configuring a device is to select a Port for the device you would like to configure.

When choosing a Port you must first select the type of Port this device will print to.

The list of Ports will vary depending on the Port type selected.

Port Type:  Enter IP Address:

Enter Port:

< Back Next > Cancel Help




# How To

## Service Documents from APPI

If using a USB cable, choose **Windows Spooler**, and choose the printer setup you need, as described earlier.

Click **Next**.



Done. Click **Finish**.





# How To

## Service Documents from APPI


### Seagull Scientific Printer Driver

In **Printers and Devices**, right-click the Zebra printer.


Right-click **Printing Preferences**

Change this screen according to your system

Click **Graphics**.



Graphics can be set to anything, but **None** seems to work best.






# How To

## Service Documents from APPI

Set according to the screen shot:




### Darkness:

Use current setting lets you set darkness on the printer

If unchecked, use Absolute  
Relative can be a little unpredictable because it adds or subtracts from current Darkness

Speed settings, use 6"/sec.







# How To

## Service Documents from APPI

In **Printers and Devices**, right-click the printer, and click **Printer Properties**. **Ports** and **Advanced** should be like these screens.

