

Document: #HT000071

Document Title: Install Labelview 9 for TEC

Product(s): Ti-1000

Procedure:

Insert CD into CD ROM DRIVE, the window shown below will come into view. Insert the USB License Key into a USB Port, then press the Down Arrow Key.

TEKLYNX' LABELVIEW Select language English -	Setting the Standard
 > LABELVIEW 9.0 > Network and User Utilities > Online Documentation > Offline Documentation > Release Note > Software Activation 	LABEL VIEW 9 is a full-featured, easy-to-use bar code and RFID label design software package. LABEL/VIEWs intuitive graphical interface allows both novice and expert users to share its power and simplicity. Over 2,100 thermal printers are supported. When you install LABEL/VIEW 9.0, the optional Form Designer and RFID tools are also installed and can be activated if you have acquired the proper license.

Select a Language then press OK.

LABELV	IEW	Setting the	
Select I	language English - English 💆		C
 LABELVIEW 9.0 LABELV Network and U Online Docume Offline Docume Release Note Software Active 	VIEW 9 - InstallShield Wizard Select the language for the installation fro English (United States)	om the choices below.	-use bar code and BEL VIEWs intuitive nd expert users to 00 thermal printers /IEW 9.0, the e also installed and e proper license.
		1 *	



Click "I Accept the Terms ", and click "Next".

TEKLY	🖓 LABELVIEW 9 - InstallShield Wizard	
	License Agreement Please read the following license agreement carefully.	
> LABE	Teklynx Newco SAS License Agreement	
> Netwo	Teklynx Newco SAS (hereafter "Teklynx") or its affiliated companies hereby grants you a non-exclusive, nontransferable license to use this software and the accompanying documentation according to the following terms:	le and ntuitive ers to
 Relea Softw 	LICENSE GRANT - You may 1) install the software on the number of computers covered by invoices for this license from Teklynx, which are hereby incorporated by reference; 2) use and transmit the software on a network within a site if authorized by an invoice from Teklynx; and	inters ed and nse.
	I accept the terms in the license agreement Print Ido not accept the terms in the license agreement	
	InstallShield	
	↓ * ∩	X

Type in your name (not required), Click "Next".

TEKLY	🛱 LABELVIEW 9 - InstallShield Wizard	X	
	Customer Information Please enter your information.		
 LABE Netwo Onlin Offlin Relea Softwo 	<u>U</u> ser Name: Organization: 		e and ituitive ers to inters ed and nse.
	InstallShield	ext > Cancel	_
		↓ ⁺	X

Click "Next".

TEKLY	🕼 LABELVIEW 9 - InstallShield Wizard	X	
	Custom Setup Select the program features you want installed.	11	
> LABE > Netwo > Onlin > Offlin > Relea > Softw	Click on an icon in the list below to change how a feature is in	nstalled. Feature Description LABELVIEW 9 This feature requires 96MB on your hard drive. It has 5 of 5 subfeatures selected. The subfeatures require 478MB on your hard drive.	le and htuitive ers to inters ed and nse.
	Install to: C:\Program Files\Teklynx\LABELVIEW 9\	Change	
	Help Space < Back	Next > Cancel	
		↓ * ∧	X

Click "Install"

> LABE > Netw > Onlin > Offlin	Image: Second State Sta	le and rtutive ers to inters
> Offlin > Relea > Softw	InstallShield	inters ed and nse.
		X

Click "Finish"



This Window will now be shown. Select the desired language, then press "OK".



Click "Next"



Select "Modify"; Click "Next"



Click "Next"

TEKLY	🔀 LABELVIEW 9 - InstallShield Wizard	×	
	Custom Setup Select the program features you want installed.		
 LABE Netwo Onlin Offlin Relea Softwood 	Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on an icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon in the list below to change how a feature is in Click on a icon i	nstalled. Feature Description LABELVIEW 9 This feature requires 0KB on your hard drive. It has 0 of 5 subfeatures selected. The subfeatures require 0KB on your hard drive.	le and htuitive ers to inters ed and nse.
	Help < Back	Next > Cancel	
		↓ + ∩	X

Click "Install"

TEKLY	Image: Base of the Program Image: Base of the Program	
 LABE Netwo Onlin Offlin Releat Softward 	The wizard is ready to begin installation. Click Install to begin the installation. If you want to review or change any of your installation settings, click Back. Click Cancel to exit the wizard.	le and ntuitive ers to inters ed and nse.
	< Back Install Cancel	
		X

Click "Finish"



Click "Activate", and "Next"



Follow the Activate Procedure.



Under "File", click "New" Icon.



Change "Use Current Printer" to "Native Printer".

Click "Add Printer"

ULABELVIEW 9 GOLD (DEMO) - Document5	identified a Country Name North Territory	
File Edit View Objects Data sources Tools W	indow Help	
New Open Save Printer Printer setup La	Image: set of the set	
	🚹 New label document	
Document5		4 Þ ×
Select	the printer you want to use with this label	5
	current printer Tec 8472,->COM11:	Î
If you	don't want to use the current printer, select another one.	
Nativ	ve Printer Tec B472,->COM11: Properties	
• Wind	Sows Printer CutePDF Writer, COM1: *	
	Add printer	
Click "Native Printer"	$\langle \cdot \rangle$	
	Next Finish Cancel	
	Click "Add Printer"	
		•
	x.v:: 0.004.0.000 cx.cv:	•

"Add Printer" window opens.

Model Port Image: Constraint of the set o	Pr	Add printer	X
Image: Section PACK & PRINT Network printers Image: Section Secti		Model ADC ADC ADC ADC ADC	Port C:\FaxPress.spl\Coverpg.pd COM1: COM2: COM3: COM3: COM4: DOT4_001 FaxPort FILE: LMIPORT: LPT1:
OK Creat Ush			Network printers

Scroll Down and select "TEC" then double-click.

DABEEVIEW SOOED (DEIVIO) - DOCUMENTS	Labert as T at a C regarded, These Microsoft Boot Renty	
File Edit View Objects Data sources Tools Window Help		
New Open Save Printer Printer setup Label/Page Print	12 12<	
IN ■ I N I N I A > N I A I ,	The magy5 → B I U = 4 = = = =	
Document5		4 ▷ ×
3 🙆 ₽		5
	Add printer	Î
	Image: Sato COM10: Image: Sato COM2: Image: Sato COM10: Image: Sato COM2: Image: Sato<	
	THAD COM6: THERMORE COM7: THERMORE COM7: THA COM9: TA Network printers Ta UR (INTERMEC) Ta Comp Top/p> Top/p>	
	CK Cancel Help	
2 3 4		, .



With the TEC Folder open select **"Tec B472"** or **"Tec B572"**, depending on your printer.

Model	Port
Tec B402A (267dpi) Tec B402G (203dpi) Tec B415 Tec B431 Tec B431 Tec B442 Tec B443 Tec B452 Tec B452 (600dpi) TEC B452 SLP Tec B452 SLP Tec B452 SLP (RFID) TEC B458 Tec B458 Tec B472 Tec B482 Tec B492 Tec B572	COM1: COM10: COM11: COM2: COM2: COM3: COM4: COM6: COM7: COM8: COM9: CPW2: Network printers

Port Setting: Select one of the "COM" Ports.

Click "OK"

After Clicking **"OK"**, the **"New Label Document"** window will appear.

	🕞 🍠 指 New label	document		
	Select the printer y	ou want to use with this label		
	© Use current printer	Tec B472,->COM11:		
X	If you don't want to u	se the current printer, select another one.		
	Native Printer	Tec B472,->COM11:	Properties	
	O Windows Printer	CutePDF Writer,COM1:		
Use Current Pri	nter		Add printer	
			[Properties
		Back	Finish Cancel	

Click on **"Use Current Printer"** which will be **"Tec B472"** or **"Tec B572"** on Port_____. This will be highlighted in blue.

Now "Click on PROPERTIES". This window will appear.

	Printer settings - Tec B472
	General Fonts
General	General Send modified data only : <off> I 30° rotation : <off> Z Flip (transparent media) : <off> Fint speed : <6.000(Inches)/s> Detection : <none (continuous="" paper)=""> Advanced Cutter</none></off></off></off>
	General Restore default settings
	OK Cancel Help



The following are steps to enter settings in "General":



On the drop-down menu click "Send modified data only".

Notice the Settings Box, it now has "ON" and "OFF" buttons; select "OFF".



Click on "180 rotation": Turn to "OFF".



Select "Flip [(transparent media]": Turn to "OFF".



Click "Temperature" then set to 3.



Click "Print speed" and set to 6.000



Click **"Advanced"** and make sure all settings are the same as above. If not, correct them using the same procedure in **"General"**.



Click **"Control codes substitution"** and make sure all settings are same as above. If not, use the same procedure as in **"General"**.

rinter settings - T	ec B472		
General Fonts			
Cutte	r	*	
Cutter : <off></off>			
Adjust cut position			
Eje	Eject last piece		
🗄 💮 Contr	ol codes substitution		
📄 🧼 Tear o	off	Ξ	
Tei	ar off : <off></off>		
Tei	ar off position		
	л •	Ŧ	
	Cuttur		
	Cutter		
مل	Restore default settings	- 11	
0			
<u>17</u>			
	OK Cancel	Help	
		- Charles	

Tear off should be "OFF".



Peel off: <ON>; Peel off position: <0.000(inches)>; Peel off sensor: <ON>

Printer settings -	Tec B472	×
General Fonts		
i	r off off eel off : <on> eel off position : <0.000(Inches)> eel-off sensor : <on> tory card tore in memory card : <off> lemory card settings</off></on></on>	* E
E ⊕ ≪ Ribb	ormat memory card on	-
	Cutter	
÷	Restore default settings	
<u> </u>	OK Cancel	Help

Memory card, Store in memory card: <OFF>



Ribbon: Print mode: <Thermal transfer>; Ribbon saver: <OFF>; Rewind motor: <0>; Feed motor: <0> Press "OK"

🕞 🎅 🎽 New label	document	••••				
Select the printer y	ou want to use with this label					
Ose current printer	Tec B472,->COM11:	Properties				
If you don't want to use the current printer, select another one.						
© Native Printer	Copy of Tec B472,COM1:	Ŧ				
© Windows Printer	CutePDF Writer,COM1:	Ţ				
	Back	Finish Cancel				

Press "Finish".

Create Your Label:



Click "New" icon.



Click "Create New Label Format".



Click the capital "A" Add Text icon.



Enter the Label information or the word **"TEST"** into Text Field. Click **"Next"**.



The TEXT can be moved by dragging it to the desired position.



Click on the blank area of the label to lock its position.



Click on "File", click "Save As" test label.

You can use this label as a template for future labels.