

Document: #HT000143

Document Title: Load ZPL Files via Zebra Setup Utilities

Product(s): Ti-1000Z

Procedure:

Zebra Setup Utilities (ZSU) is available for download <u>here</u>.

You may need to scroll down the page to find the Zebra Setup Utilities.

Install the software on a computer that is connected to the printer via USB cable (such as a laptop).

Clear labels from the Bagger.

Open ZSU.

Once set up with ZSU, make sure the printer is highlighted, and click Open Communication With Printer

This window will appear.



How To Service Documents from APPI

Click File – Open.

Browse to the file you need, and open it. This example uses the "Fonts and sizes.ZPL".



Click Send To Printer.

The Bagger will now show as having a label.

Print the label.

Direct Communication - ZDesigner 110Xi4 203 dpi (Copy 2) [ZPL]	- • ×
<u>File Edit Window Help</u>	
🗋 🚵 😂 🖉 🐁 🍇 🖀 🗶 🧇 😤 🎇 🚍 🛄 🗔 🎢 📱 📄 💆 Send To Printer	
onts and sizes.zpl	
^XA	· · · · · · · · · · · · · · · · · · ·
^FWN^PW812^T.HO. 0	
^CIO^PR6^LL812^MNN^MTT^MMR^MD25.0^JJ0,1^PON^PMN^LRN	
^LS0	
^LT0	
^SLT	
^A0N.30.30^F00.30^FD0 This is Font 0 = 30.30^FS	
^AAN,20,20^F00,70^FDA This is Font A - 20,20^FS	
^ABN,20,20^F00,100^FDB This is Font B - 20,20^FS	
^ACDN,15,15^F00,140^FDCD This is Font CD - 15,15^FS	
"AEN,15,15"FOU,1/0"FDE THIS 18 FOND E - 15,15"FS	
^AGN.0.0^F00.260^FDG Font G = 0.0^FS	
^AHN,15,15^F00,330^FDH THIS IS FONT H = 15,15^FS	
^APN,40,40^F00,360^FDP This is Font P - 40,40^FS	
^AQN,40,40^FO0,400^FDQ This is Font Q - 40,40^FS	
ARN,50,50 FOU,450 FDR INIS IS FOND R = 50,50 FS ^LSN 40 40^FOO 470^FDS This is Fond S = 40 40^FS	
^ATN,40,40^F00,520^FDT This is Font T - 40,40^FS	
^AUN,0,0^FO0,570^FDU This is Font U - 0,0^FS	
^AVN,0,0^F00,630^FDV This is Font V - 0,0^FS	
"XZ	
<	>
Data received from the printer is shown in the window below.	
4	

Note:

If your label or commands include the command to store the label on the printer, the printer screen will not show as having a label. You must load the labels from the Stored Labels screen.