

Document: #HT000147

Document Title: Zebra Designer Print Driver Port Settings

Product(s): Labelview

Procedure:

Open Windows Devices and Printers



Select and right-click on the ZDesigner 110Xi4 Print Driver





Select Printer Properties





How To Service Documents from APPI

In the General Tab, the Printer can be renamed if desired

÷ •	ZDesign	ner 110Xi4	4 203 dpi	Properties	×
Printer Settings	Stocks	Language	Barcode Fo	onts Command F	onts About
General	Sharing Po	orts Adv	vanced	Color Management	Security
-	ZDesigner	110Xi4 203 o	lpi	1	
Location:					
Comment:					
Model: Features Color: No	ZDesigner	110Xi4 203 d	pi Paper av	ailable:	
Double-si	ded: No		User de	fined	^
Speed: Un	known				
Maximum	resolution: 20	03 dpi			~
😚 Chang	e Properties	Prefe	rences	Print Te	st Page
		ОК	Cancel	Apply	Help



Select Ports Tab

Click on Add Port Button

Printer Setti	ngs S	Stocks	Langu	age	Barcode	Fonts	Command Font	s About
General	Shari	ng	Ports	Adv	anced	Color	r Management	Security
	ZDesi	gner 11	0Xi4 203	dpi (C	opy 1)			
Print to ti checked	port.	escrinti	on on	cumer	Printer	rint to t	the first free	^
CON	11. Se	rial Po	rt.		THT S	COM	1.	
	12: Se	rial Po	rt			COM		
CON	15: Se	rial Po	rt					
FILE:	Pr	int to F	ile					
WSD	-C W	SD Por	t		Parts			
USB0	Vi	rtual p	rinter por	rt for	ZDesig	ner 110	OXilll Plus 200D	Ы
USBC	Vi	rtual p	rinter po	rt for	ZDesig	ner 11	0Xi <mark>4 2</mark> 03 dpi (Co	op 🗸
Ac	ld Port.			Delet	e Port		Configure P	ort
✓ Enable	bidirec printer	tional : poolin	support 19					



Select New Port Button

1	Printer Ports ×
Available port types:	
doPDF 7 Monitor	
HP Universal Port Monitor Local Port Standard TCP/IP Port ZDesigner Port Monitor	
New Port Type	New Port Cancel

Enter required information.

Port Name	ravanced		it com	garation	
Name:	LAN_				
TCP/IP Data	а				
Printer Name	e or IP Address	r:			
Port Number	r.	9100			

Click OK