



How To

Service Documents from APPI

Document: #HT000168

Document Title: Store Labels on the T-375

Product(s): T-375

Foreword:

Note: This procedure ONLY works with Labelview 8.5 and earlier. Also, this procedure requires that only the LabelView driver is in use.

Procedure:

1. In the T-375 Touch Screen go to the "Labels" Screen.
2. Touch "Print" to "Off" and "Clear Labels".
3. In LabelView go to **Edit, Label Setup, Options,**
4. **Settings, Layout.**
5. Check mark the box "Store Layout In Printer".
6. "Memory" must be "Flash E".
7. Un-check the box "Use Layout Name"
8. Click on "OK"
9. And the next screen Click on "OK"
10. Go to "File" "Print" and send 1 label.
11. In "Layout Name" screen, type in a maximum 3-digit number associated with that label.
12. (Do Not include a "0" zero before any numbers,
13. choose numbers like 555 or 333).
14. Click on "OK"
15. In the T-375 "Stored Labels" screen "Labels" green.
16. Turn "OFF" to "Print" "No Labels" red.
17. Input **Stored Label Number.**
18. "Labels" green.
19. Cycle T-375 to print the Stored Label.