

Document: #HT000155

Document Title: Store and Print Labels for Crosstex T-1000

Product(s): T-1000

Procedure:

Zebra Setup Utilities

Zebra Setup Utilities (ZSU) is available for download <u>here</u>.

You may need to scroll down the page to find the **Zebra Setup Utilities**.

Install the software on a computer that is connected to the printer via USB cable (such as a laptop).

Open ZSU.

Once set up with **ZSU**, make sure your printer is highlighted, and click "**Open Communication With Printer**".

	ZDesigner 110Xi US800 1	4 203 dpi		ZDesigner (Copy 1) USB002	110Xi4 203 dpi	^	Install New Printer
	ZDesigner 110X/ (Copy 2) USB003	4 203 dpi	P	ZDesigner (Copy 3) US8006	110Xi4 203 dpi	I	Refresh Printer List
	ZDesigner 110Xi (Copy 4) USB007	4 203 dpi		ZDesigner (Copy 5) US8008	110Xi4 203 dpi		
nter Configu	ation						
nter Configu	ration ure the selected printer Configure P	rinter Settings	5		D ov	vnload For	nts and Graphics
nter Configu	ration ure the selected printer Configure P	rinter Settings Print Quality	5		Too	vnload For	nts and Graphics



This window will appear.

How To Service Documents from APPI

Go to "File – Open".



Browse to where your .ZPL files are saved.

Select 1.ZPL and click "Open".

8	C)pen	×
€ ∋ - ↑ 🔳	Desktop >	✓ C Sea	rch Desktop 🔎
Organize 🔻 Nev	v folder		· · · · · · · · · · · · · · · · · · ·
🔆 Favorites	Name Siz	te Item type	Date modified
	🏷 1.ZPL	1 KB ZPL File	8/13/2015 12:50 PM
E Desktop	🏷 3.ZPL	1 KB ZPL File	8/13/2015 11:48 AM
🥽 Libraries	🏷 88.ZPL	1 KB ZPL File	8/12/2015 3:38 PM
Documents	🏷 98.ZPL	1 KB ZPL File	8/12/2015 3:30 PM
🌙 Music	🏷 99.ZPL	1 KB ZPL File	8/13/2015 1:02 PM
Pictures	🗸 🐎 GYOW.zpl	1 KB ZPL File	5/8/2015 10:56 AM 🗸
1.ZPL ZPL File	Date modified: 8/13/2015 12:50 PM Size: 326 bytes	M Date created: 8/13/20)15 11:07 AM
	File <u>n</u> ame: 1.ZPL	✓ All	files (*.*) v Open Cancel

Your screen will have the contents of 1.ZPL on it.

Click "Send To Printer".

There will be no response from the printer.

a	Dir	ect Comn	nunicatio	ion - ZDe	esigner	r 110Xi4	4 203 dp	oi (Copy	y 4) [ZPL]	-	 ×
File Edit	Window	Help									
🗋 👌 🗐 🗍	n % 🖬 🕯	X	👻 😤	80] 🗔 🖪	1 .		Sen Sen	d To Printer		
1.ZPL									Send To Pri	inter (F5)	×
∱XA omev									_		^
^DFE:99.21	PL										
^FWN^CFD,	4^PW812^LH0	,0									
^CI0^PR6^1	L406^MNN^MI	T^MMR^MI	025.0^J	JJO,1,0	,f,e^P	PON^PMN	I^LRN				
^LSO											
^LT0											
^SL1.1^FS											
^FC%											
^AON, 45, 40	5^F0171,181^	FVLOT %c	1/%m/%y	7 %I:%M	:%S 1	^FS					
^AON, 45, 45	orF0631,1810	SN00001,	,1,Y^FS	5							
~F0181,261											
-BXN, 5, 200) (e / e e.T e.)										
TVLOI %0/	-em/-eV €1:€W	1.42 1.42	2								
TUT											~
<											>

How To Service Documents from APPI

Go to "File – Close".

Repeat these steps and load **3.ZPL**.

8		Dir	ect Communication - ZDesigner 110Xi4 203 dpi (Copy 4) [ZPL]	□ ×
F	ile Edit	Window	Help	
	New	Ctrl+N	🛛 📐 🧇 😤 🎇 🚍 🛄 🛄 🎒 📱 🖺 🖺 🦄 Send To Printer	
2	Open	Ctrl+0		×
	Close	Ctrl+F4		•
	Save	Ctrl+S		
	Save As			
3	Send To Printe	er F5	MMR^MD25.0^JJ0,1,0,f,e^PON^PMN^LRN	
	Export Last Re	cieved Data		
	Export All Rec	ieved Data		
	Exit		LOT &d/&m/&v &I.&M.&S 1 ^FS	
^A	ON, 45, 45^B	70631,181^	5N00001,1,Y^FS	
^F	0181,261			
AB AF	XN,5,200 VLOT %d/%n	n/%v %I:%M	:%S 1^FS	
^F	'D1			
<				>

On the T-1000, go to "Printer Settings – Stored Labels".

If this box says "**Reprint ON**", or "**Overwrite**", press it until it says "**Reprint OFF**".

Press the Green Button labeled "Label #".

Type in **1** or **3**. The label will load, and you can start printing.

